

# Ethernet Low Power PoE Switches

## NSW2020-10T-LPOE-IN



## Features

- Multiple working modes to address your business needs: Default(Normal mode), EXTEND(Surveillance mode)
- Support port traffic control
- Up to 250m transmission distance on Extend mode
- Support buffer optimization
- All metal housing, safe and reliable

## Specifications

Model	NSW2020-10T-LPOE-IN
Hardware Specification	
Ports Type	10×100Mbps network ports (RJ45), including 8 PoE ports
Standards	IEEE802.3, IEEE802.3u, IEEE802.3az, IEEE802.3x, IEEE802.3af, IEEE802.3at
Switching capacity	2 Gbps
Forwarding performance	1.49Mpps
Packet Buffer	448K bit
MAC	1K
Dimensions (W×D×H)	171*103*25mm
Weight	0.29KG

Power Supply	DC:48/51V
Max.Power	65W
PoE	802.3at/af (4/5+, 7/8-)
Max. PoE Power	Max capacity: 60 W, Max capacity for single port: 30 W
Prior Ports	1 to 2
Cooling Fans	0
Operating temperature	0 °C to 40 °C (32 °F to 104 °F)
Operating humidity	10%~90% (non-condensing)
Indicator	POWER Steady on: AC input is normal, POWER Off: No AC input, PoE-MAX off: The POE power supply power of the whole machine is less than 80% of the specification, PoE-MAX Steady on : The POE power supply power of the whole machine is greater than 85% of the specification, LINK/ACT Off: No link, LINK/ACT Steady on: Linked, LINK/ACT Flashing: Transmitting data, No PoE Indicator
Working Mode	Default (Normal mode) : All ports can communicate with each other, EXTEND (Surveillance mode): Transmission distance up to 250 meters

## Ordering Info

Product Model	Description
NSW2020-10T-LPOE-IN	Unmanaged Ethernet Switch(PoE)

### Zhejiang Uniview Technologies Co., Ltd.

No. 369, Xietong Road, Xixing Sub-district, Binjiang District, Hangzhou City, 310051, Zhejiang Province, China

Email: overseasbusiness@uniview.com; globalsupport@uniview.com

<http://www.uniview.com>

©2023-2025 Zhejiang Uniview Technologies Co., Ltd. All rights reserved.

\*Product specifications and availability are subject to change without notice.

\*Despite our best efforts, technical or typographical errors may exist in this document. Uniview cannot be held responsible for any such errors and reserves the right to change the contents of this document without prior notice.