

Chime

ED-R1-NB



Overview

The ED-R1 is a wireless chime mainly used with ED-525B-WB dual-lens video doorbells.

Features

- Simple installation, plug and play.
- 5-level volume adjustment, 3 ringtones available.
- Supports connection to doorbell through Sub-1 GHz.

Specifications

Model	ED-R1-NB
Chime	
Connection method	Sub-1 GHz
Speaker	Built-in speaker
General	
Power source	As per definitions by different countries/regions
Installation method	Install the plug directly into the socket
Dimensions	53.6 mm × 85.6 mm × 39.8 mm
Weight	Net weight: 80g Gross weight: 125g
Power consumption	3W
Button	From left to right: volume adjustment, reset status, change ringtone
Operating temperature	-20 °C to 50 °C

Dimensions

